



DENON AVC-X3700

Denon AVC-X3700H giúp trải nghiệm phim ảnh với âm thanh sống động và chính xác.

Thông số

Number of Power Amps	9	
Power Output	180 watts per channel (6 ohms, 1 kHz, THD: 1 ch driven)	1%,
	135 watts per channel (6 ohms, 1 kHz, THD: 2 ch driven)	0.7%,
	165 watts per channel (6 ohms, 1 kHz, THD: 2 ch driven)	0.7%,
	105 watts per channel (8 ohms, 20Hz–20kHz, THD: 0.08%, 2 ch driven)	
Speaker Impedance	4-16Ω/ohms	
Preamplifier Section		
Input Sensitivity/ Impedance	200 mV/47k kohms	
Frequency Response	10Hz–100kHz – +1, -3 dB (Direct Mode)	
S/N Ratio	100 dB (IHF-A weighted, Direct Mode)	

FM Section	
Tuning Frequency Range	87.5 - 107.9 MHz
AM Section	
Tuning Frequency Range	520–1710 kHz
General	
Power Supply	120V/60 Hz
Power Consumption	660W (Standby 0.1W, CEC standby 0.5W)
Power Consumption (No Sound)	60W (ECO Mode On) 100W (ECO Mode Off)
Maximum Dimensions (WxDxH)	
Antenna:Horizontal (in)	17.1 x 15.3 x 6.6
Antenna:Vertical (in)	17.1 x 15.3 x 9.3
w/o Antenna: (in)	17.1 x 14.9 x 6.6
Carton Dimensions (Packaging) (WxDxH) (in)	21.2 x 19.0 x 10.1
Weight (lbs)	27.6
Weight (Packaging) (lbs)	33.3

Ports		
In	HDMI	x7
	8K HDMI	x1
	Component (Video)	x2
	Composite (Video)	x3
	Phono	x1
	Analog Audio	x5
	Digital Coaxial	x2
	Digital Optical	x2
	USB Front	x1
Out	HDMI Monitor (eARC)	x3
	8K HDMI	x2
	Component (Video)	x1
	Composite Monitor	x2
	Audio Pre-out (SW)	11.2ch
	Zone 2 (pre-out and speaker assignable)	x3
	Headphones	x1
Other	Ethernet	x1
	Microphone Port	x1
	FM/AM Tuner Antenna	x1