



## DENON AVC-X6700

Denon AVC-X6700H giúp trải nghiệm phim ảnh với âm thanh sống động và chính xác.

### Thông số

Number of Power Amps	11	
Power Output	205 watts per channel (6 ohms, 1 kHz, THD: 1 ch driven)	1%,
	175 watts per channel (6 ohms, 1 kHz, THD: 2 ch driven)	0.7%,
	140 watts per channel (8 ohms, 20Hz–20kHz, THD: 0.05%, 2 ch driven)	
Speaker Impedance	4-16Ω/ohms	
<b>Preamplifier Section</b>		
Input Sensitivity/Impedance	200 mV	
Frequency Response	10Hz–100kHz – +1, -3 dB (Direct Mode)	
S/N Ratio	100 dB (IHF-A weighted, Direct Mode)	

<b>FM Section</b>		
Tuning Frequency Range	87.5–107.9 MHz	
<b>AM Section</b>		
Tuning Frequency Range	520–1710 kHz	
<b>General</b>		
Power Supply	120V/60 Hz	
Power Consumption	750W (Standby 0.1W, CEC standby 0.5W)	
Power Consumption (No Sound)	65W (ECO Mode On) 110W (ECO Mode Off)	
Maximum Dimensions (WxDxH)		
Antenna:Horizontal (in)	17.1 x 15.3 x 6.6	
Antenna:Vertical (in)	17.1 x 15.3 x 9.3	
w/o Antenna: (in)	17.1 x 14.9 x 6.6	
Carton Dimensions (Packaging) (WxDxH) (in)	20.9 x 18.3 x 11.9	
Weight (lbs)	32.0	
Weight (Packaging) (lbs)	37.9	

<b>Ports</b>		
<b>In</b>	HDMI (Front + 1)	x7 + 1
	8K HDMI	x1
	Component (Video)	x2
	Composite (Video)	x4
	Phono	x1
	Analog Audio	x6
	Digital Coaxial	x2
	Digital Optical	x2
	USB Front	x1
	<b>Out</b>	HDMI Monitor (eARC)
8K HDMI		x2
Component (Video)		x1
Composite Monitor		x2
Audio Pre-out (SW)		132ch
<b>Other</b>	Zone Out	x3
	Headphones	x1
	Ethernet	x1
	Microphone Port	x1
	FM/AM Tuner Antenna	x1