



## PASION10-PAK

Loa Karaoke JBL Pasion 10 Loa dễ hát, đầy giọng tốt, dễ ghép ampli liền vang.

### Thông số

<b>SYSTEM TYPE:</b>	10", 3-way, bass-reflex
<b>FREQUENCY RANGE (-10 dB)<sup>1</sup>:</b>	50 Hz - 17 kHz
<b>FREQUENCY RESPONSE (±3 dB)<sup>1</sup>:</b>	65 Hz - 14 kHz
<b>SENSITIVITY (1W@1M)<sup>1</sup>:</b>	90 dB
<b>NOMINAL IMPEDANCE:</b>	8 Ohms
<b>MAXIMUM SPL<sup>2</sup>:</b>	113 dB (119 dB peak)
<b>POWER RATING<sup>3</sup>:</b>	200 W/400 W/800 W
<b>(CONTINUOUS/PROGRAM/PEAK)</b>	
<b>COVERAGE PATTERN:</b>	120° × 90° (H × V)

<b>DIMENSIONS (H × W × D):</b>	292 mm × 521 mm × 320 mm 11.5 inch × 20.5 inch × 12.6 inch
<b>NET WEIGHT:</b>	11 Kg (24.3 lbs)
<b>LF DRIVER:</b>	1 × 10" Woofer
<b>HF DRIVER:</b>	4 × 3" Tweeter
<b>INPUT CONNECTORS:</b>	Binding Post
<b>ENCLOSURE CONSTRUCTION:</b>	Vinyl covered MDF
<small>1 Full space (4) conditions 2 Calculated maximum SPL based on rated power handling 3 IEC standard, pink noise with 6 dB crest factor for 100 hours</small>	